

Intex Lumo® 20 Watt Rechargeable LED Worklight - SLB20

Product Description:

Intex LED Work Lights designed for cool non-glare work-site illumination, featuring advanced Chips-On-Board technology to deliver true representation of colours, optimised colour temperature and even beam patterns, improving lighting effect and efficiency.

Specifications:

| | |
|--------------------------|------------|
| Code | SLB20 |
| Lumens | 2200/1100 |
| Run Time | 3/6 Hours |
| Charge Time | 5 Hours |
| Battery | 7.4V/7.8Ah |
| Charger | DC 8.4V 2A |
| Water Resistant Rating | IP67 |
| Impact Resistance Rating | IK09 |
| Warranty | 12 Months |

AS/NZS 60598.2.4:2005 Inc A1 - AS/NZS 60598.1:2013 AS/NZS 60598.2.5:2002 - AS/NZS 61347.2.13:2013 - AS/NZS 61347.1:2016

Contents:

20W LED WorkLight
7.4V/7.8Ah Li-Ion Battery Pack
8.4V/2A Charger
8.4V/1A Car Charger
Instruction Manual

Battery & Power Instructions:

- Charge battery for at least 8 hours before first use.
- Red indicator on lamp means 'charging in process'.
- Green indicator on lamp means 'charging complete'.
- Always fully charge to extend battery life.
- Do not leave battery in full discharged condition.
- Recharge Work Light at least once in every 30 days.
- Do not charge Work Light if wet or damp.
- Only use original and genuine Intex cords and chargers.

Warnings:

- Wear safety goggles (user and bystanders).
- Avoid looking directly into light beam.
- Do not use Work Light near open flames.
- Do not cover LED lens when operating, to prevent overheating.
- Do not contaminate LED lens with organic solvents.
- Take care to position Work Light in a careful manner to ensure the light is properly supported by the stand.
- After adjusting Work Light stand angle be sure to tighten the stands adjustment screw.
- When using Work Light at heights take additional precautions to ensure safe use and prevent falling objects causing harm to bystanders and equipment.